

SERIES 41 CIRCULATION HEATER

Zerostart[®]

The Series 41 tank heater provides dependable engine start by circulating warmed coolant through the engine.

BENEFITS

- Provides a quick start
- Convenient and easy installation
- Durable construction
- Provides overheat protection
- Easy and convenient to service

WHERE TO USE

- Industrial
- Agriculture
- Off-Road



FEATURES

- Copper heating element
- Replaceable thermostat and element
- 5/8" inlet and outlet
- Vertical installation
- Heavy duty 3-wire attached cord

PHILLIPS & TEMRO
industries[®]

phillipsandtemro.com

SERIES 41 CIRCULATION HEATER




Thermostat Range: Opens at 190°F (88°C) Closes at 150°F (66°C)

Product Dimensions: 2 3/4" x 8 1/2" (7 x 22 cm)

Cord Length: 5' (1.5m)

Plug Type: NEMA 5-15



Part No.	Watts	Volts	Amps	Plug Configuration	Inlet/Outlet Size	Replacement Element	Thermostat	Certifications
2204010	750	120	6.25	NEMA 5-15	5/8"	2204061	2204266	CSA
2204029	1000	120	8.33	NEMA 5-15	5/8"	2204088	2204266	CSA
2204037	1500	120	12.5	NEMA 5-15	5/8"	2204096	2204266	CSA




Thermostat Range: Opens at 205°F (96C) Closes at 165°F (74°C)

Product Dimensions: 4 5/16" x 12 5/16" (11 x 31 cm)

Cord Length: 22" (56 cm)

Plug Type: NEMA 5-20



Part No.	Watts	Volts	Amps	Plug Configuration	Inlet/Outlet Size	Replacement Element	Thermostat	Certifications
3300091	2000	120	16.7	NEMA 5-20	5/8"	3300093	3300097	CSA